

ADJ ENCORE PROFILE PRO WW **DMX TRAITS: CHANNEL FUNCTIONS & VALUES**

Supports Software Versions: ≥ 1.03				
Features subject to change without notice.				
MODE/CHANNEL			VALUE	FUNCTION
2CH	3CH	6CH		
1	1	1		Dimmer Intensity 8bit
			000-255	0 to 100%
2	2	2	000-255	Dimmer Fine 16bit
				Shutter
			000-031	Shutter Closed (LEDs OFF)
			032-063	Shutter OPEN (LEDs ON)
			064-095	Strobe effect slow to fast
			096-127	Shutter OPEN (LEDs ON)
			128-159	Pulse effect in sequences
			160-191	Shutter OPEN (LEDs ON)
			192-223	Random strobe effect slow to fast
			224-255	Shutter OPEN (LEDs ON)
				Dim Modes
			000-020	Default to Unit Setting
			021-040	Standard
			041-060	Stage
			061-080	TV
			081-100	Architectural
			101-120	Theatre
			121-140	Stage 2
				Dimming Speed
			141	0.1Sec.
			142	0.2Sec.
			143	0.3Sec.
			144	0.4Sec.
			145	0.5Sec.
			146	0.6Sec.
			147	0.7Sec.
			148	0.8Sec.
			149	0.9Sec.
			150	1.0Sec.
			151	1.5Sec.
			152	2.0Sec.
			153	3.0Sec.
			154	4.0Sec.
			155	5.0Sec.
			156	6.0Sec.
			157	7.0Sec.
			158	8.0Sec.
			159	9.0Sec.
			160	10Sec.
			161-255	Default to Unit Setting
				Dim Curves
			000-020	Square
			021-040	Linear
			041-060	Inv. Squa
			061-080	S. Curve
			081-255	No Function

ADJ ENCORE PROFILE PRO WW **DMX TRAITS: CHANNEL FUNCTIONS & VALUES**

Supports Software Versions: ≥ 1.03				
Features subject to change without notice.				
MODE/CHANNEL			VALUE	FUNCTION
2CH	3CH	6CH		
		6		LED Refresh Rates
			000-028	1200 HZ LED Refresh Rate (Default)
			029-029	1080 Hz LED Refresh Rate
			030-030	1090 Hz LED Refresh Rate
			031-031	1100 Hz LED Refresh Rate
			032-032	1110 Hz LED Refresh Rate
			033-033	1120 Hz LED Refresh Rate
			034-034	1130 Hz LED Refresh Rate
			035-035	1140 Hz LED Refresh Rate
			036-036	1150 Hz LED Refresh Rate
			037-037	1160 Hz LED Refresh Rate
			038-038	1170 Hz LED Refresh Rate
			039-039	1180 Hz LED Refresh Rate
			040-040	1190 Hz LED Refresh Rate
			041-041	1210 Hz LED Refresh Rate
			042-042	1220 Hz LED Refresh Rate
			043-043	1230 Hz LED Refresh Rate
			044-044	1240 Hz LED Refresh Rate
			045-045	1250 Hz LED Refresh Rate
			046-046	1260 Hz LED Refresh Rate
			047-047	1270 Hz LED Refresh Rate
			048-048	1280 Hz LED Refresh Rate
			049-049	1290 Hz LED Refresh Rate
			050-050	1300 Hz LED Refresh Rate
			051-051	1310 Hz LED Refresh Rate
			052-052	1320 Hz LED Refresh Rate
			053-053	1330 Hz LED Refresh Rate
			054-054	1340 Hz LED Refresh Rate
			055-055	1350 Hz LED Refresh Rate
			056-056	1360 Hz LED Refresh Rate
			057-057	1370 Hz LED Refresh Rate
			058-058	1380 Hz LED Refresh Rate
			059-059	1390 Hz LED Refresh Rate
			060-060	1400 Hz LED Refresh Rate
			061-061	1410 Hz LED Refresh Rate
			062-062	1420 Hz LED Refresh Rate
			063-063	1430 Hz LED Refresh Rate
			064-064	1440 Hz LED Refresh Rate
			065-065	1450 Hz LED Refresh Rate
			066-066	1460 Hz LED Refresh Rate
			067-067	1470 Hz LED Refresh Rate
			068-068	1480 Hz LED Refresh Rate
			069-069	1490 Hz LED Refresh Rate
			070-070	1500 Hz LED Refresh Rate
			071-071	2500 Hz LED Refresh Rate
			072-072	4000 Hz LED Refresh Rate
			073-073	5000 Hz LED Refresh Rate
			074-074	6000 Hz LED Refresh Rate
			075-075	10K Hz LED Refresh Rate
			076-076	15K Hz LED Refresh Rate
			077-077	20K Hz LED Refresh Rate
			078-078	25K Hz LED Refresh Rate
			079-079	Disable LED Refresh Rate
			080-255	No Function