

# QuickQ DIN



Product Code: CS100702

The intuitive simplicity of QuickQ software in a space-saving DIN rail mount solution.

QuickQ DIN supports all QuickQ features including Events, 10Scene and Executes, making it ideal for any installation where space is at a premium and control in a small package is required.

Control up to 4 universes of DMX from its two RDM-enabled DMX ports and easily build installed lighting control systems with connectivity features that include inbuilt Wi-Fi for programming and remote control, and four 10Scene ports for connecting up to forty 10Scene wall plates.

## Specifications

### Hardware Specification

- Universes supported: 4
- Direct DMX Outputs Phoenix Screw Terminal: 2
- External Monitor: 1920 x 1080 HDMI
- Inbuilt Wi-Fi: Yes
- Network Port: 1
- USB Ports: 2
- Power Input: 12v DC

### Software Specifications

- Max Number of DMX Channels: 2048
- Max Number of Fixtures Supported: 2048
- OSC Supported: Yes
- RDM Autopatch for fast show patching
- Fixture library of over 48,000 fixture files
- Built in FX generator
- Colour picker and Gel inbuilt Gel library
- RDM Autopatch for fast show patching
- Offline designer software available for Windows and Mac
- Supported fixtures: All - LEDs, Dimmers & Moving Lights

### Included Accessories:

- Wi-Fi Antenna: 1
- DIN Rail Mount Clips: 2
- 10Scene Connectors: 4
- 12v Power Supply: 1

### DIN Weights and Dimensions:

- Width : 200mm (7.8 inches)
- Depth: 165mm (6.5 inches)
- Height: 40mm (1.6 inches)
- Weight: 0.65kg (1.43lb)

### Boxed Weights and Dimensions:

- Width: 268mm (10.5 inches)
- Depth: 220mm (8.7 inches)
- Height: 130mm (5.1 inches)
- Weight: 1.04kg (2.29 lb)