



DE980TN 8Ω

HF Drivers - 1.4 Inches











- 220 W continuous program power capacity
- 1.4" horn throat diameter
- 75 mm (3 in) aluminium voice coil
- Titanium diaphragm
- 500 18000 Hz response
- 108.5 dB sensitivity
- Neodymium magnet assembly with shorting copper cap

The DE980TN is the latest version of our 75mm (3.0 in) voice coil, neodymium high frequency driver. The diaphragm in this model has been completely redesigned to incorporate a bent edge voice coil former, new dome and surround geometry and an optimized phase plug. These modifications combine to better control diaphragm displacement and deformations, resulting in lower distortion and a smoother higher frequency response above 10kHz.

DE980TN

HF Drivers- 1.4 Inches





SPECIFICATIONS¹

Throat Diameter	36 mm (1.4 in)			
Nominal Impedance	8 Ω			
Minimum Impedance	8.1 Ω			
Nominal Power Handling ²	110 W			
Continuous power handling ³	220 W			
Sensitivity (1W/1m) ⁴	108.5 dB			
Frequency Range	0.5 - 18.0 kHz			
Recommended Crossover ⁵	1.2 kHz			
Voice Coil Diameter	75 mm (3.0 in)			
Winding Material	Aluminium			
Inductance	0.1 mH			
Diaphragm Material	Titanium			
Flux Density	2.05 T			
Magnet Material	Neodymium Ring			

MOUNTING AND SHIPPING INFO

Four M6 holes 90° on 102 r	nm (4 in) diameter
Overall Diameter	131 mm (5.2 in)
Depth	54 mm (2.13 in)
Net Weight	2.3 kg (5.1 lb)
Shipping Units	1
Shipping Weight	2.35 kg (5.17 lb)
Shipping Box 140x135x62 mm	(5.51x5.31x2.44 in)
Other Details 4x M6 Mounting Studs with included	bolts and washers

Replacement diaphragm

SERVICE KIT

MMD3DTN8M

1.	Driver	mounted	on	B&C	ME	90	horn.

^{2. 2} hour test made with continuous pink noise signal within the range from the recommended crossover frequency to 20 kHz. Power calculated on rated 2. 2 hour test made with continuous pink noise signal within the range from the receminimum impedance.
3. Power on Continuous Program is defined as 3 dB greater than the Nominal rating.
4. Applied RMS Voltage is set to 2.83 V for 8 ohms Nominal Impedance.
5. 12 dB/oct. or higher slope high-pass filter.