MagicDMX Full



Product Code: 100-072 (Single), 100-070 (Set of 10)

The MagicDMX Full USB to DMX Interface offers a full universe of DMX control with RDM support and without any time limit. It has the option of being used either as Output, or as an Input enabling use for monitoring DMX. Remotely set DMX addresses, select fixture modes and auto patch RDM compliant fixtures to MagicQ.

Features

- One Universe DMX output
- 5 pin female XLR
- USB-C connector
- Basic electrical protection
- LED status indicator

Specifications

Hardware Specification

- DMX Port(s): 1
- RDM Support: Yes
- USB Port(s): 1 (USB-C)
- Unlocks 'demo mode features: No
- Time Restriction: No

Software Specifications

- Universes: 64
- Channels: 32,768
- Number of fixtures: upto 32,768
- Cues: 5000
- Cue stacks: 2000
- Palettes: 4096
- Groups: 5000
- Media server support: 50 (each different content)

Weights and Dimensions

- Width:135mm (5.3")
- Depth: 93mm (3.6")
- Height: 38mm (1.4")
- Weight (MagicDMX Inside case): 0.1kg (0.22lbs)

ChamSys