

FXPar 6

Spin up spectacular party lighting effects with six independently controlled RGBW zones and the RGB outer ring of FXpar 6. Take control with DMX to create custom eye candy, let dynamic sound-activated programs generate instant eye-catching effects, or use the optional IRC-6 remote to wirelessly call up your choice of static colors and high-energy looks.

HIGHLIGHTS

- Compact effect par with multiple technologies in a single fixture
- Independent control of the wash RGBW wash LEDs and RGB outer ring for creating dynamic effects
- Create spectacular effects with 6 zones of control
- Generate eye-catching effects with sound-activated and automated programs
- Easily control static colors and automated programs with the optional IRC-6 remote
- Save time running cables and extension cords by power linking multiple units
- Flicker-free video operation suitable for on-camera use
- Fits best in the CHS-40 VIP Gear Bag



SPECIFICATIONS

- DMX Channels : 3, 6, or 11
- DMX Connectors : 3-pin XLR
- Beam Angle : 20°
- Field Angle : 36°
- Illuminance : 5,657 lux @ 2 m
- Lumens : 3,239
- Power Linking : 8 units @ 120 V; 12 units @ 230 V
- Input Voltage : 100 to 240 VAC, 50/60 Hz (auto-ranging)
- Power and Current : 63 W, 0.9 A @ 120 V, 60 Hz
- Weight : 3.0 lb (1.3 kg)
- Size : 10.8 x 2.7 x 12 in (275 x 69 x 305 mm)
- Approvals : CE, RoHS
- Light Source : 18 LEDs (quad-color RGBW) 52 W, (1 A), 50,000 hours life expectancy.
- Light Source (ring) : 51 LEDs (RGB) 6 W, (0.5 A), 50,000 hours life expectancy Strobe Rate: 0 to 20 Hz
- Bracket Mounting Hole : 13 mm
- Optional Controllers : IRC-6

WHAT'S INCLUDED

- FXpar 6
- Power cable
- Quick Reference Guide