

Shocker FX

- Versatile blinder, wash and strobe light with brilliant eye candy effects
- 12 controllable sections (8 RGB + 4 white) allow for creative programming flexibility
- Trigger eye-catching effects via Master/Slave, DMX, or the optional IRC-6 remote
- Combine zone control and special effect macros for stunning visual impact
- Save time running cables and extension cords by power linking multiple units
- Easily transport in the optional CHS-25 VIP gear bag



Specifications

- DMX Channels: 8, 18, 30, or 43
- DMX Connectors: 3-pin XLR
- Light Source: 280 LEDs (tri-color) 50 W total, (1.5 A), 50,000 hours life expectancy
- Light Source: 56 LEDs (cool white), 11 W total (0.8 A), 50,000 hours life expectancy
- Strobe Rate: 0 to 20 Hz
- Beam Angle: 97°
- Field Angle: 139°
- Illuminance: 219 lux @ 2 m
- Lumens : 1,981
- Power Linking: 12 units @ 120 V; 20 units @ 230 V
- Input Voltage: 100 to 240 VAC, 50/60 Hz (auto-ranging)
- Power and Current: 45 W, 0.6 A @ 120 V, 60 Hz
- Power and Current: 45 W, 0.4 A @ 230 V, 50 Hz
- Weight: 2.0 lb (1 kg)
- Size: 10.2 x 2.8 x 6.3 in (260 x 70 x 160 mm)
- Approvals: CE, RoHS

