

WELL CONNECT

FEATURES

- **Wireless Control Hub:** Compact, battery-powered Bluetooth and W-DMX/CRMX transceiver designed to control WELL fixtures or any DMX lighting system.
- **App-Driven Operation:** Pairs seamlessly with the ConnectFX app on iOS and Android for intuitive wireless control of scenes and effects.
- **Flexible Output Options:** Supports both wireless & wired DMX protocols, offering reliable signal distribution for any setup.
- **12-Hour Battery Life:** Integrated lithium-ion battery delivers all-day wireless operation; USB-C port provides continuous power when needed.
- **Onboard Playback:** Trigger pre-programmed scenes directly from the unit's display—no console required.
- **Rugged & Road-Ready:** Durable aluminum housing and M12 threaded bolt ensure quick, secure mounting in demanding environments.
- **Smart Firmware Management:** Web-based UI allows for easy firmware updates and configuration.



SPECIFICATIONS

CONSTRUCTION / PHYSICAL

- Dimensions: 6.89 x 7.01 x 2.56 in (175 x 178 x 65 mm)
- Weight: 1.8 lb (0.9 kg)
- Exterior Color: Black
- Housing Material: Aluminum alloy

CONNECTIONS

- Power Input: USB-C
- Data Connectors: 5-pin XLR IN/OUT, USB-A Female, RJ45

CONTROL

- Control Protocol: Chauvet CONNECT app, Art-Net, DMX, W-DMX, sACN

ELECTRICAL

- Input Voltage: 5 VDC, 2A via USB-C

BATTERY

- Battery type: Lithium Ion
- Rechargeable: Yes
- Battery Charge Time: 8 hours
- Battery Life: 12 hours
- Battery Power: 12 V, 24 Ah

CERTIFICATIONS / QUALIFICATIONS

- CE, FCC, UKCA
- IP Rating: IP20, dry location
- Temperature (Ambient): -4 °F to 113 °F (-20 °C to 45 °C)

WHAT'S INCLUDED

- WELL CONNECT
- EPSU USB-A
- USB-A to USB-C cable

OPTIONAL ACCESSORIES

- VIP Signal Distributor, VIP Media Server